

# 1SC0450V2A0-45 and 1SC0450V2A0-65

## Preliminary Data Sheet

Single-Channel Cost-Effective SCALE™-2 IGBT Driver Core with Fiber-Optic Interface for 4500V and 6500V IGBTs

### Abstract

The 1SC0450V2A0-xx features versatile fiber-optic links and drives all usual high-power IGBT modules up to 4500V or 6500V. Thanks to its high output power capability, a single 1SC0450V2A0-xx driver can drive up to four parallel-connected 4500V or 6500V IGBT modules and consequently provides easy inverter design covering higher power ratings. Multi-level topologies involving 3300V or 4500V IGBTs with higher isolation requirements can also be easily supported by 1SC0450V2A0-xx.

The 1SC0450V2A0-xx combines a complete single-channel driver core with all components required for driving, such as an isolated DC/DC converter, short-circuit protection, Advanced Active Clamping as well as supply voltage monitoring. Enhanced features such as gate boosting or power supply short-circuit protection are also implemented and provide further driving benefits.

The driver's secondary side is electrically isolated from its primary side. The 1SC0450V2A0-45 meets the requirements of 4500V IGBT applications while the 1SC0450V2A0-65 covers the requirements of 6500V IGBT applications.

An output current of 50A and 6W drive power is available, making the 1SC0450V2A0-xx an ideal driver platform for universal use in medium and high-power applications. The driver provides a gate voltage swing of 15V/-10V. The turn-on voltage is regulated to maintain a stable 15V regardless of the output power level.

Its outstanding EMC allows safe and reliable operation even in harsh industrial applications.

### Product Highlights

- ✓ Ultra-compact single-channel driver
- ✓ Highly integrated SCALE™-2 chipset
- ✓ Gate current  $\pm 50A$ , 6W output power
- ✓ 15V/-10V gate driving
- ✓ Blocking voltages up to 4500V or 6500V
- ✓ Basic isolation to IEC 61800-5-1 and IEC 60664-1
- ✓ Short signal propagation delays
- ✓ UL-compliant
- ✓ Lead-free

### Applications

- ✓ Traction
- ✓ Railroad power supplies
- ✓ Light rail vehicles
- ✓ HVDC
- ✓ Flexible AC transmission systems (FACTS)
- ✓ Medium-voltage converters
- ✓ Wind-power converters
- ✓ Industrial drives
- ✓ Medical applications

---

## Preliminary Datasheet

### Safety Notice!

The data contained in this data sheet is intended exclusively for technically trained staff. Handling all high-voltage equipment involves risk to life. Strict compliance with the respective safety regulations is mandatory!

Any handling of electronic devices is subject to the general specifications for protecting electrostatic-sensitive devices according to international standard IEC 60747-1, Chapter IX or European standard EN 100015 (i.e. the workplace, tools, etc. must comply with these standards). Otherwise, this product may be damaged.

### Important Product Documentation

This data sheet contains only product-specific data. For a detailed description, must-read application notes and important information that apply to this product, please refer to "1SC0450V Description & Application Manual" on [www.power.com/igbt-driver/go/1SC0450](http://www.power.com/igbt-driver/go/1SC0450).

### Mechanical Dimensions

Dimensions: Refer to the "1SC0450V Description & Application Manual"

### Fiber-Optic Interfaces

| Interface             | Remarks                              | Part type #  |
|-----------------------|--------------------------------------|--------------|
| Drive signal input IN | Fiber-optic receiver (Notes 1, 2)    | HFBR-2522ETZ |
| Status output OUT     | Fiber-optic transmitter (Notes 1, 3) | HFBR-1522ETZ |

## Preliminary Datasheet

### Absolute Maximum Ratings

| Parameter                       | Remarks  | Min  | Max          | Unit                     |
|---------------------------------|--|------|--------------|--------------------------|
| Supply voltage $V_{DC}$         | VDC to GND   | 0    | 16           | V                        |
| Supply voltage $V_{CC}$         | VCC to GND   | 0    | 16           | V                        |
| Logic output voltage $V_{SO}$   | SO to GND  | -0.5 | $V_{CC}+0.5$ | V                        |
| SO current                      | Failure condition, total current (Note 30)               |      | 20           | mA                       |
| Gate peak current $\hat{I}_G$   | Note 4   | -50  | +50          | A                        |
| External gate resistance        | Turn-on and turn-off (Notes 4, 5)                        | 0.3  |              | $\Omega$                 |
| Average supply current $I_{DC}$ | Notes 6, 7   |      | 860          | mA                       |
| Output power                    | Ambient temperature $\leq 70^\circ\text{C}$ (Notes 8, 9) |      | 8            | W                        |
|                                 | Ambient temperature $\leq 85^\circ\text{C}$ (Note 8)     |      | 6            | W                        |
| Gate boosting output power      | Notes 8, 10  |      | 4            | W                        |
| Gate charge $Q_{GBS}$           | GBS to GH  |      | 15           | nC                       |
| Bias current $I_{GBS}$          | On-state   |      | 20           | $\mu\text{A}$            |
| Switching frequency $f$         |  |      | 10           | kHz                      |
| Power supply short-circuit time | Non-repetitive (Note 25)                                 |      | 1            | s                        |
| Test voltage (50Hz/1min.)       | Primary to secondary (Note 19)                           |      | 10.2         | $\text{kV}_{\text{eff}}$ |
| $ dV/dt $                       | Rate of change of input to output voltage                |      | 35           | $\text{kV}/\mu\text{s}$  |
| Operating voltage               | Primary/secondary, 1SC0450V2A0-45                        |      | 4500         | $V_{\text{peak}}$        |
|                                 | Primary/secondary, 1SC0450V2A0-65                        |      | 6500         | $V_{\text{peak}}$        |
| Operating temperature           | Notes 9  | -40  | +85          | $^\circ\text{C}$         |
| Storage temperature             |  | -40  | +85          | $^\circ\text{C}$         |

### Recommended Operating Conditions

| Power Supply            | Remarks    | Min  | Typ | Max  | Unit |
|-------------------------|------------|------|-----|------|------|
| Supply voltage $V_{DC}$ | VDC to GND | 14.5 | 15  | 15.5 | V    |
| Supply voltage $V_{CC}$ | VCC to GND | 14.5 | 15  | 15.5 | V    |

## Preliminary Datasheet

|                                   |
|-----------------------------------|
| <b>Electrical Characteristics</b> |
|-----------------------------------|

All data refer to +25°C and  $V_{CC} = V_{DC} = 15V$  unless otherwise specified.

| Power Supply                            | Remarks                             | Min  | Typ  | Max  | Unit |
|---|-------------------------------------|------|------|------|------|
| Supply current $I_{DC}$                 | Without load                        |      | 110  |      | mA   |
| Supply current $I_{CC}$                 |                                     |      | 20   |      | mA   |
| Coupling capacitance $C_{io}$           | Primary to output, total            |      | 8    |      | pF   |
| Supply voltage VGB                      | VGB to VISO (Note 26)               |      | 25   |      | V    |
| VGB charge                              | VGB to VISO (Note 27)               |      | 540  |      | nC   |
| Power Supply Monitoring                 | Remarks                             | Min  | Typ  | Max  | Unit |
| Supply threshold $V_{CC}$               | Primary side, clear fault           | 11.6 | 12.6 | 13.6 | V    |
|   | Primary side, set fault (Note 16)   | 11.0 | 12.0 | 13.0 | V    |
| Monitoring hysteresis                   | Primary side, set/clear fault       | 0.35 |      |      | V    |
| Supply threshold $V_{ISO}-V_E$          | Secondary side, clear fault         | 11.8 | 12.6 | 13.4 | V    |
|   | Secondary side, set fault (Note 17) | 11.2 | 12.0 | 12.8 | V    |
| Monitoring hysteresis                   | Secondary side, set/clear fault     | 0.35 |      |      | V    |
| Supply threshold $V_E-V_{COM}$          | Secondary side, clear fault         |      | 5.2  |      | V    |
|   | Secondary side, set fault (Note 17) |      | 4.9  |      | V    |
| Monitoring hysteresis                   | Secondary side, set/clear fault     |      | 0.3  |      | V    |
| Power Supply Protection                 | Remarks                             | Min  | Typ  | Max  | Unit |
| Overload power threshold                | Output, set fault (Note 23)         |      | 17   |      | W    |
| Fault feedback pulse                    | Fiber-optic OUT (Note 24)           | 500  |      |      | μs   |
| Logic Outputs                           | Remarks                             | Min  | Typ  | Max  | Unit |
| SO pull-up resistor to VCC              | On board                            |      | 10   |      | kΩ   |
| SO output voltage $V_{SO}$              | Failure condition, $I(SO) < 6.5mA$  |      |      | 0.7  | V    |
| GBS voltage                             | GBS to GH, on-state (Note 26)       |      | 9    |      | V    |
|   | GBS to GH, off-state (Note 26)      |      | 0    |      | V    |
| Short-Circuit Protection                | Remarks                             | Min  | Typ  | Max  | Unit |
| $V_{CE}$ -monitoring threshold          | Factory set value (Note 21)         |      | 10.2 |      | V    |
| Minimum response time                   | Note 14                             |      | 5.1  |      | μs   |
| Delay to clear fault state $T_{d(cfs)}$ | After IGBT short circuit (Note 15)  |      | 8    |      | μs   |
| Delay in IGBT turn-off $T_{cshd}$       | Factory-set value (Note 22)         |      | 0.2  |      | μs   |

## Preliminary Datasheet

| Timing Characteristics              | Remarks      | Min | Typ | Max  | Unit |
|-------------------------------------|--------------|-----|-----|------|------|
| Turn-on delay $T_{d(on)}$           | Note 11      |     | 135 |      | ns   |
| Turn-off delay $T_{d(off)}$         | Note 11      |     | 105 |      | ns   |
| Output rise time $T_{r(GH)}$        | Note 12      |     | 30  |      | ns   |
| Output fall time $T_{f(GL)}$        | Note 12      |     | 25  |      | ns   |
| Transmission delay of fault state   | Note 18      |     | 150 |      | ns   |
| Acknowledge delay time $T_{d(ack)}$ | Note 28      |     | 220 |      | ns   |
| Acknowledge pulse width $T_{(ack)}$ | On host side | 400 | 700 | 1050 | ns   |

| Electrical Isolation               | Remarks   | Min  | Typ | Max | Unit              |
|------------------------------------|---|------|-----|-----|-------------------|
| Test voltage (50Hz/1s)             | Primary to secondary side (Note 19)             | 10.2 |     |     | kV <sub>eff</sub> |
| Partial discharge extinction volt. | Primary to secondary side                       |      |     |     |                   |
|                                    | 1SC0450V2A0-45 (Note 20)                        | 5400 |     |     | V <sub>peak</sub> |
|                                    | 1SC0450V2A0-65 (Note 20)                        | 7800 |     |     | V <sub>peak</sub> |
| Creepage distance (Note 29)        | On the PCB                                      |      |     |     |                   |
|                                    | Primary to secondary side (Material group IIIa) | 45   |     |     | mm                |
| On the transformer                 | Primary to secondary side (Material group I)    | 36   |     |     | mm                |
|                                    | Clearance distance                              | 25   |     |     | mm                |

| Output               | Remarks              | Min | Typ  | Max | Unit |
|----------------------|----------------------|-----|------|-----|------|
| Blocking capacitance | VISO to VE (Note 13) |     | 18.8 |     | μF   |
|                      | VE to COM (Note 13)  |     | 9.4  |     | μF   |

### Output Voltage Swing

The output voltage swing consists of two distinct segments. First, there is the turn-on voltage  $V_{GH}$  between pins GH and VE.  $V_{GH}$  is regulated and maintained at a constant level for all output power values and frequencies.

The second segment of the output voltage swing is the turn-off voltage  $V_{GL}$ .  $V_{GL}$  is measured between pins GL and VE. It is a negative voltage. It changes with the output power to accommodate the inevitable voltage drop across the internal DC/DC converter.

| Output Voltage             | Remarks            | Min | Typ  | Max | Unit |
|----------------------------|--------------------|-----|------|-----|------|
| Turn-on voltage, $V_{GH}$  | Any load condition |     | 15.0 |     | V    |
| Turn-off voltage, $V_{GL}$ | No load            |     | -9.5 |     | V    |
| Turn-off voltage, $V_{GL}$ | 6W output power    |     | -9.0 |     | V    |
| Turn-off voltage, $V_{GL}$ | 8W output power    |     | -8.8 |     | V    |

---

## Preliminary Datasheet

### Footnotes to the Key Data

- 1) The transceivers required on the host controller side are not supplied with the gate driver. It is recommended to use the same types as used in the gate driver. For product information, refer to [www.power.com/igbt-driver/go/fiberoptics](http://www.power.com/igbt-driver/go/fiberoptics).
- 2) The recommended transmitter current at the host controller is 20mA. A higher current may increase jitter or delay at turn-off.
- 3) The typical transmitter current at the gate driver is 20.5mA. In case of supply undervoltage, the minimum transmitter current at the gate driver is 15mA: this is suitable for adequate plastic optical fibers with a length of up to 10 meters.
- 4) The maximum peak gate current refers to the highest current level occurring during the product lifetime. It is an absolute value and also applies to short pulses.
- 5) Twice the given minimum resistance value must be inserted between the interface connectors GH and GL. Moreover, the given minimal resistance value must be used in the full gate turn-on (interface connector GH to gate) and turn-off (interface connector GL to gate) path.
- 6) The average supply input current is limited for thermal reasons. Higher values than specified by the absolute maximum rating are permissible (e.g. during power supply start up) if the average remains below the given value, provided this average is taken over a time period which is shorter than the thermal time constants of the driver in the application.
- 7) There is no protection against light overload of the power supply. In the case of start-up with very high blocking capacitor values, or of short circuit/heavy overload at the output, the supply input current is limited internally. The time during which the driver output is shorted/overloaded must be limited externally and must be within the absolute maximum rating.
- 8) The maximum output power must not be exceeded at any time during operation. It must also be observed for time periods shorter than the thermal time constants of the driver in the application.
- 9) An extended output power range is specified in the output power section for ambient temperatures limited from -40°C to 70°C.
- 10) The gate-boosting output power can be calculated according to "1SC0450V Description & Application Manual" and is specified as a part of the gate driver's total output power, which is the sum of the turn-on power over the output GH plus the gate-boosting power over the output VGB. The turn-on power approximately equals the turn-off power of the output GL. The gate boosting is not active at turn-off.
- 11) Including the delay of the external fiber-optic links (cable length: 1m). Measured from the transition of the turn-on or turn-off command at the optical transmitter on the host controller side to the direct output of the gate drive unit (excluding the delay of the gate resistors). The delay time is measured between 50% of the input signal and the 10% voltage swing of the corresponding output. The delay time is independent of the output loading.
- 12) Output rise and fall times are measured between 10% and 90% of the nominal output swing with an output load of 4.7Ω and 270nF. These values are given for the driver side of the gate resistors. The time constant of the output load in conjunction with the present gate resistors leads to an additional delay at the load side of the gate resistors.
- 13) External blocking capacitors should be placed between the VISO and VE as well as the VE and COM terminals. Refer to "1SC0450V Description & Application Manual" (paragraph "DC/DC output (VISO), emitter (VE) and COM terminals)" for recommendations. Ceramic capacitors are recommended.
- 14) The minimum response time is valid for the circuit given in the description and application manual with the values of the corresponding tables.
- 15) Measured on the host side. The fault status on the secondary side is extended by the "delay in IGBT turn-off" and automatically reset after the specified time. Refer to "1SC0450V Description & Application Manual" for more details.
- 16) Undervoltage monitoring of the primary-side supply voltage (VCC to GND). If the voltage drops below this limit, a fault is transmitted to the SO output.
- 17) Undervoltage monitoring of the secondary-side supply voltage (VISO to VE and VE to COM, which correspond to the approximate turn-on and turn-off gate-emitter voltages). If the corresponding voltage drops below this limit, a fault is transmitted to the fiber-optic output and the IGBT is switched off after the corresponding delay. Refer to "1SC0450V Description & Application Manual" for more

---

## Preliminary Datasheet

- details.
- 18) Delay of external fiber-optic links. Measured from the driver secondary side (ASIC output) to the optical receiver on the host controller with a 1m cable.
  - 19) HiPot testing (= dielectric testing) must generally be restricted to suitable components. This gate driver is suited for HiPot testing. Nevertheless, it is strongly recommended to limit the testing time to 1s slots. Excessive HiPot testing at voltages much higher than 3182V<sub>AC,rms</sub> with 1SC0450V2A0-45 and 4596V<sub>AC,rms</sub> with 1SC0450V2A0-65 may lead to insulation degradation. No degradation has been observed over 1min. testing at 10.2kV<sub>AC,rms</sub>. Every production sample (transformer only) shipped to customers has undergone 100% testing at the given value for 1s.
  - 20) Partial discharge measurements are performed in accordance with IEC 60270 and IEC 60664-1 for basic insulation requirements.
  - 21) The V<sub>CE</sub>-monitoring threshold value can be reduced with an external resistor. Refer to "1SC0450V Description & Application Manual".
  - 22) The turn-off event of the IGBT after a secondary-side fault (IGBT short circuit, undervoltage monitoring or power-supply short circuit/overload) can be additionally delayed with an external capacitor. Refer to "1SC0450V Description & Application Manual".
  - 23) Gate turn-on and turn-off current pulses in normal operation do not affect the power supply protection. This protection is only triggered by a corresponding power-supply overload or short circuit (which would also occur in case of gate-emitter short circuit/overload).
  - 24) The fault feedback pulse length/pattern depends on the power supply short-circuit/overload. The minimum value applies for any power-supply overload.
  - 25) Maximum short-circuit duration of the driver output. The driver's power supply VDC must be switched off externally within the given time. The power supply protection prevents the driver's components from being damaged within the given time frame. For details refer to the driver's "1SC0450V Description & Application Manual".
  - 26) The voltage values of the pins VGB resp. GBS are correspondingly about 50V and 34V respectively referred to COM. This must be considered for the design of the creepage and clearance distances.
  - 27) The given value applies for a full discharge of VGB to VISO at turn-on, when no external capacitor is used. It can be increased by using additional external capacitors.
  - 28) Including the delay of the external fiber-optic links (cable length: 1m). Measured from the transition of the turn-on or turn-off command at the optical transmitter on the host controller side to the transition of the acknowledge signal at the optical receiver on the host controller side.
  - 29) Creepage distances over additional components (e. g. fiber-optic wires, fixation screws, ...) which are not part of the driver must be taken into account by the user.
  - 30) Including current flowing into the on-board pull-up resistor of 10kΩ.

### Legal Disclaimer

The statements, technical information and recommendations contained herein are believed to be accurate as of the date hereof. All parameters, numbers, values and other technical data included in the technical information were calculated and determined to our best knowledge in accordance with the relevant technical norms (if any). They may base on assumptions or operational conditions that do not necessarily apply in general. We exclude any representation or warranty, express or implied, in relation to the accuracy or completeness of the statements, technical information and recommendations contained herein. No responsibility is accepted for the accuracy or sufficiency of any of the statements, technical information, recommendations or opinions communicated and any liability for any direct, indirect or consequential loss or damage suffered by any person arising therefrom is expressly disclaimed.

---

## Preliminary Datasheet

### Ordering Information

The general terms and conditions of delivery of Power Integrations Switzerland GmbH apply.

| Type Designation | Description |
|------------------|-------------|
|------------------|-------------|

|                |  |
|----------------|--|
| 1SC0450V2A0-45 | Single-channel SCALE-2 driver core for 4500V IGBTs |
| 1SC0450V2A0-65 | Single-channel SCALE-2 driver core for 6500V IGBTs |

Product home page: [www.power.com/igbt-driver/go/1SC0450](http://www.power.com/igbt-driver/go/1SC0450)

Refer to [www.power.com/igbt-driver/go/nomenclature](http://www.power.com/igbt-driver/go/nomenclature) for information on driver nomenclature.

---

### Information about Other Products

**For other drivers, product documentation, and application support:**

Please click: [www.power.com](http://www.power.com)

---

### Manufacturer

Power Integrations Switzerland GmbH  
Johann-Renfer-Strasse 15  
2504 Biel-Bienne, Switzerland

Phone +41 32 344 47 47  
Fax +41 32 344 47 40  
Email [igbt-driver.sales@power.com](mailto:igbt-driver.sales@power.com)  
Website [www.power.com/igbt-driver](http://www.power.com/igbt-driver)

© 2014...2015 Power Integrations Switzerland GmbH.

All rights reserved.

We reserve the right to make any technical modifications without prior notice.

Version 1.0 from 2016-05-20



---

Preliminary Datasheet

**Power Integrations Worldwide High Power Customer Support Locations**

**World Headquarters**

5245 Hellyer Avenue  
 San Jose, CA 95138 | USA  
 Main +1 408 414 9200  
 Customer Service:  
 Phone +1 408 414 9665  
 Fax +1 408 414 9765  
 Email [usasales@power.com](mailto:usasales@power.com)

**Switzerland (Biel)**

Johann-Renfer-Strasse 15  
 2504 Biel-Bienne | Switzerland  
 Phone +41 32 344 47 47  
 Fax +41 32 344 47 40  
 Email [igbt-driver.sales@power.com](mailto:igbt-driver.sales@power.com)

**Germany (Ense)**

HellwegForum 1  
 59469 Ense | Germany  
 Phone +49 2938 643 9990  
 Email [igbt-driver.sales@power.com](mailto:igbt-driver.sales@power.com)

**Germany (Munich)**

Lindwurmstrasse 114  
 80337 Munich | Germany  
 Phone +49 895 527 39110  
 Fax +49 895 527 39200  
 Email [eurossales@power.com](mailto:eurossales@power.com)

**China (Shanghai)**

Rm 2410, Charity Plaza, No. 88  
 North Caoxi Road  
 Shanghai, PRC 200030  
 Phone +86 21 6354 6323  
 Fax +86 21 6354 6325  
 Email [chinasales@power.com](mailto:chinasales@power.com)

**China (Shenzhen)**

17/F, Hivac Building, No 2,  
 Keji South 8th Road,  
 Nanshan District  
 Shenzhen | China, 518057  
 Phone +86 755 8672 8725  
 Fax +86 755 8672 8690  
 Hotline +86 400 0755 669  
 Email [chinasales@power.com](mailto:chinasales@power.com)

**Italy (Milano)**

Via Milanese 20, 3rd. Fl.  
 20099 Sesto San Giovanni | Italy  
 Phone +39 024 550 8701  
 Fax +39 028 928 6009  
 Email [eurossales@power.com](mailto:eurossales@power.com)

**UK (Herts)**

First Floor, Unit 15, Meadway Court,  
 Rutherford Close, Stevenage,  
 Herts SG1 2EF | United Kingdom  
 Phone +44 1252 730 141  
 Fax +44 1252 727 689  
 Email [eurossales@power.com](mailto:eurossales@power.com)

**India (Bangalore)**

#1, 14th Main Road  
 Vasanthanagar  
 Bangalore 560052 | India  
 Phone +91 80 4113 8020  
 Fax +91 80 4113 8023  
 Email [indiasales@power.com](mailto:indiasales@power.com)

**Japan (Kanagawa)**

Kosei Dai-3 Bldg., 2-12-11, Shin-  
 Yokohama, Kohoku-ku, Yokohama-shi,  
 Kanagawa 222-0033 | Japan  
 Phone +81 45 471 1021  
 Fax +81 45 471 3717  
 Email [japansales@power.com](mailto:japansales@power.com)

**Korea (Seoul)**

RM 602, 6FL  
 Korea City Air Terminal B/D, 159-6  
 Samsung-Dong, Kangnam-Gu  
 Seoul 135-728 | Korea  
 Phone +82 2 2016 6610  
 Fax +82 2 2016 6630  
 Email [koreasales@power.com](mailto:koreasales@power.com)

**Taiwan (Taipei)**

5F, No. 318, Nei Hu Rd., Sec. 1  
 Nei Hu Dist.  
 Taipei 11493 | Taiwan R.O.C.  
 Phone +886 2 2659 4570  
 Fax +886 2 2659 4550  
 Email [taiwansales@power.com](mailto:taiwansales@power.com)